



XP 95

Intelligent Smoke and Heat Detectors

The XP 95 range has an elegant, unobtrusive design, finished in pure white polycarbonate



- *Open, Digital Protocol*
- *Alarm Flag for fast alarm reporting*
- *Alarm Address for fast location of alarm*
- *Automatic addressing with patented XPERT Card*
- *Electronics Free Base*
- *Slide-Easy Base*
- *Ease of installation*
- *Elegant Design*

The XP95 range of intelligent fire detectors is advanced in design, improved in performance and has unique features that benefit the installer and end user. The open, digital protocol product has remained basically unchanged since its inception in 1986. An open protocol allows freedom of choice for the fire system specifier, installer and end user. A system using a digital protocol is also much less susceptible to corruption than an analogue protocol and is therefore often preferred in a system which is life critical.

XP95 detectors have been carefully researched and developed and the range has undergone rigorous testing to ensure that it meets not only European and other standards but also the demands of today's high technology environments.

A unique, patented address mechanism, the XPERT card, ensures that the address data is stored in the base while keeping the base free of electronic parts that could be damaged during installation.



XP95 Ionisation Smoke Detector

The air in the dual chambers of the XP95 ionisation smoke detector is irradiated to produce ions that travel to the positive and negative electrodes and hence create a current flow in the chambers. Smoke entering the outer chamber causes a drop in the current flow and an increase in the voltage measured at the junction between the outer and inner chambers. The analogue voltage signal produced in the sensing chamber is converted to a digital signal by the electronic circuitry and transmitted to the control equipment on interrogation. The micro-processor in the control equipment then compares the signal with the stored data and initiates a pre-alarm or fire alarm as smoke density increases. When the equipment determines that a fire condition exists, it instructs the detector to switch on its indicator LED and the pre-planned alarm routine is initiated.

03-A-048



XP95 Multisensor Detector

The XP95 Multisensor detector combines inputs from optical and heat sensors and processes them using a sophisticated algorithm. It is designed to be sensitive to a wide range of fires and may be used in place of an ionisation detector in many instances. The detector's construction is similar to that of the optical detector but uses a different lid and optical mouldings to accommodate the thermistor temperature sensor.

03-A-039



XP95 Heat Detector

The XP95 heat detector is distinguishable from the smoke detectors by its low air-flow resistance case which allows good contact between the sensing thermistor and the surrounding air. The device monitors temperature by using a single thermistor network which provides a voltage output proportional to the external air temperature. The voltage signal is processed and transmitted to the control equipment in exactly the same way as in the case of the ionisation smoke detector. A heat detector for use in ambient safe temperatures of up to 50°C and which reaches the alarm level at 90°C is also available.

03-A-049 (standard)

03-A-049A (high temperature)



XP95 Optical Detector

The XP95 optical smoke detector uses an internal pulsing LED and a photo-diode at an obtuse angle. In clear air conditions the photo-diode in the XP95 detector receives no light from the LED and produces a corresponding analogue signal. The signal increases when smoke enters the chamber and light is scattered onto the photo-diode. The signal is processed by the electronic circuitry and transmitted to the control equipment in exactly the same way as in the case of the ionisation smoke detector. The optical smoke detector is externally identical to the ionisation detector but is distinguished by having a clear indicator LED which emits red light when the detector is in alarm.

03-A-050



XP95 Beam Detector

XP95 beam detectors are designed to protect large open spaces such as museums, churches, and warehouses. Two versions are available: one comprises a separate transmitter and receiver plus an interface to the loop; the other is a reflecting version which has the transmitter and receiver in one unit. Both versions are loop-powered.

03-A-040A (end to end)

03-A-040B (50m)

03-A-040C (100m)



The XP95 flame detector is designed for use in areas where flaming fires may be expected and is sensitive to low-frequency, flickering infra-red radiation emitted by flames during combustion. The XP95 flame detector is loop-powered and requires no external supply. It communicates with the control panel using either the XP95 or Discovery open, digital protocol.

03-A-041

Please note, the flame detector is not supplied with a bracket



Intrinsic Safe Detector

XP95 Intrinsic Safe (IS) detectors include all the benefits of the standard XP95 range, but are developed specifically for use in hazardous areas.

This range includes ionisation and optical smoke detectors, heat d approved to E EX ia IIC T5.

XP95 IS detectors, manual call points and short circuit isolators are approved by a number of marine classification societies. These include the American Bureau of Shipping (ABS), Bureau Veritas (BV), Det Norske Veritas (DNV), Germanischer Lloyd, Lloyd's Register of Shipping, and the Maritime and Coastguard Agency (MCA).



Sounders, Beacons & Sounder Beacons

There is a wide choice of devices for audible and visual alarm signalling. Sounders and beacons are available separately and as a combined sounder beacon unit.

03-A-043 100dB Loop Sounder



Interfaces for Intelligent Systems

A comprehensive range of interface units is available. Please contact us for details.



XP95 Manual Call Point

When activated, the XP95 manual call point not only interrupts the polling cycle to indicate to the control panel that it has been operated, but also reports its address. Thus an alarm and its condition can be reported in less than 0.2 seconds.

03-A-053 (surface mounting)

03-A-054 (flush mounting)



Isolating Base

The XP95 20D Isolating base senses and isolates short circuit faults on XP95 loops and spurs. The base is loop powered, polarity sensitive and accepts the patented XPERT card to set the associated device address.

03-A-045

XP95 Isolator

Isolators are designed to protect the XP95 loop in the event of a short circuit fault. They divide a loop of fire detectors and ancillary devices into groups of 20 as a rule, so that, in the event of a short circuit, no more than 20 devices will be inoperable. The XP95 isolator has particularly low nonisolating resistance.

03-A-046

03-A-052 (isolator base)

Bases

A wide range of bases is available. Please contact us for details.



XP95 Mounting base and patented XPERT Card

The base has been designed to enable detectors to be plugged in without any need for force and to have a "one-way-only" fit. By means of a unique, patented "XPERT" card the address information is held in the base while keeping the base entirely free of electronic parts. This coded plastic card is inserted into the base on commissioning, so that the address remains the same, no matter how often the detector is replaced by similar devices for servicing purposes.

03-A-047

Automatic Addressing with the patented XPERT Card

Depending on the combination of pips removed, switches in the detector head are operated to produce the correct address, when the detector head is inserted.

XP95 Specification Summary

Typical at 23 C and 24VDC unless other stated	XP95 Multisensor	XP95 Isolating base	XP95 Ionisation	XP95 Optical	XP95 Temperature	XP95 High Temp	XP95 MCP	XP95 Isolator
Device Part No	03-A-039	03-A-045	03-A-048	03-A-050	03-A-049	03-A-049A	03-A-053/056	03-A-046
Base Part No	03-A-047	N/A	03-A-047	03-A-047	03-A-047	03-A-047	N/A	03-A-052
Size of Device in Base Height x Diameter (mm)	58x100	24x100	50x100	50x100	50x100	50x100	Surface 87x87x52 Flush 87x87x31	32x100
Supply Voltage	17-28VDC	17-28VDC	17-28VDC	17-28VDC	17-28VDC	17-28VDC	17-28VDC	17-28VDC
Quiescent Current	500µA	43µA	280µA	340µA	250µA	250µA	230µA	45µA
Normal Surge Current (Synchronised to ADC Operation)	1mA	N/A	1mA	1mA	1mA	1mA	1mA	N/A
Alarm Indication	Red LED Clear in quiescent state	N/A	Red LED	Red LED Clear in quiescent state	Red LED	Red LED	Red LED	N/A
Alarm LED Current	4mA	N/A	2mA	4mA	2mA	2mA	2mA	N/A
Normal Operating Temperature (no icing)	-20 to +60°C	-20 to +60°C	-20 to +60°C	-20 to +60°C	-20 to +70°C	-20 to +70°C	-20 to +60°C	-20 to +70°C
Humidity (no condensation)	0-95%RH	0-95%RH	0-95%RH	0-95%RH	0-95%RH	0-95%RH	0-95%RH	0-95%RH
Max wind (continuous)	N/A	N/A	10m/s	N/A	N/A	N/A	N/A	N/A

XP95 smoke and heat detectors have been approved by a number of approvals bodies throughout the world including, LPCB in the UK and VdS in Germany. They comply with the EMC directive 89/336/EEC and CE marked. XP95 detectors are UL listed.



Wire-Free Protection Limited, t/a WFP (Fire & Security)
Unit 8 Oaklands Farm Estate, Goatsmoor Lane, Stock, Essex CM4 9RS

Tel: 0845 481 0307 Fax: 0845 481 0309
sales@w-fp.co.uk w-fp.co.uk