



Series 65

Wide voltage conventional fire detectors

Series 65 has been developed from the highly successful Series 60 range of conventional detectors



- *Wide operating voltage*
- *Advanced electronic technology*
- *Flashing LED option*
- *Magnetic test switch option*
- *Can be used on security systems*
- *Electrically compatible with Series 60*
- *Mechanically compatible with Series 60*
- *Proven detection performance*
- *Designed to meet approvals worldwide*
- *Range of bases available*

Series 65 incorporates well-proven sensing technologies, together with advances in materials and electronics technology, including an IC based on that used in XP95 analogue addressable detectors.

Having a wide operating voltage of 9-33V, the Series 65 detectors can be integrated into security systems, when used with a relay base.

The Series 65 wide voltage range consists of ionisation, integrating ionisation and optical smoke detectors, four grades of heat detector and a range of bases. The detectors are identical in appearance to Series 60.

Each type of detector is available in three versions:

- a standard version
- a version with an LED which flashes continuously in quiescent mode
- and one with both a flashing LED and a magnet-operated test switch (reed relay)

Series 65 has been tested and approved to the following standards:

EN54-7:2000 - optical and ionization smoke detectors

EN54-5:2000 - heat detectors



Series 65 Ionisation Smoke Detector

The sensing part of the detector consists of two chambers - an open, outer chamber and a semi-sealed reference chamber within. Mounted in the reference chamber is a low activity radioactive foil of Americium 241 which enables current to flow between the inner and outer chambers when the detector is powered up. As smoke enters the detector, it causes a reduction of the current flow in the outer chamber and hence an increase in voltage measured at the junction between the two chambers. The voltage increase is monitored by the electronic circuitry which triggers the detector into the alarm state at a preset threshold. An externally visible red LED lights up when the detector changes to alarm state.

An **integrating ionisation detector**, suitable for use in areas where transient levels of smoke may be expected, is also available.



Series 65 Bases

The bases have been designed to enable detectors to be plugged in without any need for force - particularly useful when fitting to suspended ceilings. **All Series 65 bases are lockable.**

The standard base is identical to the Series 60 base, so uses the same part number, 03-NA-037A. It contains no electronic parts which could be damaged during installation.

Relay Bases

Application

Series 65 relay bases are primarily intended for use with control units using 4-wire detector supply and alarm initiating circuits. Where local codes allow, they may also be used in 2- and 4-wire circuits to provide volt-free control signals to an auxiliary system such as an automatic door closer. They are not suitable for use in systems where it is specified or required that operation of the auxiliary system shall be fail safe and must not be used with any other type of detector.

The standard Series 65 relay base, 03-NA-037R, provides one set of volt-free, changeover (form C) contacts that change state when the detector signals an alarm.

Auxiliary relay base, 03-NA-037B, provides two sets of volt-free changeover contacts to facilitate the switching of a remote LED or other auxiliary device.

EOL (end of line) relay bases are intended for use with 4-wire circuits and feature two sets of changeover contacts and a power supervision relay. Part numbers: 03-NA-037C for circuits having a supply voltage between 9 and 18 volts DC and 03-NA-037D for circuits having a supply voltage between 16 and 33 volts DC.

12V relay base, 03-NA-037E, is designed for use in both fire and security systems. For fire systems a jumper on the PCB is fitted to a "latching" position. For security systems the jumper is moved to another position so that the base is non-latching.



Series 65 Optical Smoke Detector

Optical smoke detectors incorporate a pulsing LED located in a chamber within the housing of the detector. The chamber is designed to exclude light from any external source. At an angle to the LED is a photo-diode which normally does not register the column of light emitted by the LED. In the event of smoke from a fire entering the chamber, the light pulse from the LED will be scattered and hence registered by the photo-diode. If the photo-diode "sees" smoke on the two following pulses, the detector changes into the alarm state and the indicator LED lights up. The detector housing is identical to that of the ionisation detector but has an indicator LED which is clear in quiescent state but produces red light in alarm.

Series 65 Heat Detector

The A1R, BR and CR (rate of rise) heat detectors operate by using a matched pair of thermistors to sense heat. One thermistor is exposed to the ambient temperature, the other is sealed. In normal conditions the two thermistors register similar temperatures, but, on the development of a fire, the temperature recorded by the exposed thermistor will increase rapidly, resulting in an imbalance, causing the detector to change into the alarm state. Rate-of-rise detectors are designed to detect a fire as the temperature increases, but they also have a fixed upper limit at which the detector will go into alarm if the rate of temperature increase has been too slow to trigger the detector earlier.

The CS (static response) heat detector has only one thermistor and changes to the alarm state at a preset temperature. Externally, the heat detectors are distinguishable from the smoke detectors by having wide openings to the surrounding atmosphere to allow good movement of air around the external thermistor.



Specification Summary

Series 65 Ionisation smoke detectors Detector	Series 65 Ionisation/ Integrating Ionisation	Series 65 Ionisation/ Integrating Ionisation	Series 65 Ionisation/ Integrating Ionisation
Features	Standard	Flashing LED	Flashing LED/Reed switch
Part Number	03-NA-032A/03-NA-061	03-NA-032B/03-NA-062	032-NA-032C/03-NA-063
Supply Voltage	9 to 33V	9 to 33V	9 to 33V
Average quiescent current at 24V	28µA	45µA	45µA
Average quiescent current at 9V	16µA	21µA	21µA
Alarm current at 24V	52mA	52mA	52mA
Alarm current at 9V	17mA	17mA	517mA
Alarm indication	Red LED	Red LED	Red LED
Normal operating temperature (no condensation or icing)	-20 to +60°C	-20 to +60°C	-20 to +60°C
Max wind continuous	10m/s	10m/s	10m/s
Remote output (R-) characteristics	Current sink to -ve line, limited to 17mA <i>Note: when using a remote indicator a current-limiting resistor may be required</i>		
Series 65 optical smoke detectors Detector	Series 65 Optical	Series 65 Optical	Series 65 Optical
Features	Standard	Flashing LED	Flashing LED/Reed switch
Part Number	03-NA-033A	03-NA-033B	03-NA-033C
Supply Voltage	9 to 33V	9 to 33V	9 to 33V
Average quiescent current at 24V	40µA	45µA	45µA
Average quiescent current at 9V	35µA	40µA	40µA
Alarm current at 24V	52µA	52µA	52µA
Alarm current at 9V	17µA	17µA	17µA
Alarm indication	Clear LED, Red in alarm	Clear LED, Red in alarm	Clear LED, Red in alarm
Normal operating temperature (no condensation or icing)	-20 to +60°C	-20 to +60°C	-20 to +60°C
Max wind continuous	Not affected	Not affected	Not affected
Remote output (R-) characteristics	Current sink to -ve line, limited to 17mA <i>Note: when using a remote indicator a current-limiting resistor may be required</i>		
Series 65 heat detectors Detector	Heat Class A1R	Heat Class A1R	Heat Class A1R
Features	Standard	Flashing LED	Flashing LED/Reed switch
Part Number	03-NA-034A	03-NA-035A	03-NA-036A
Supply Voltage	9 to 33V	9 to 33V	9 to 33V
Average quiescent current at 24V	45µA	55µA	55µA
Average quiescent current at 9V	40µA	50µA	50µA
Alarm current at 24V	52µA	52µA	52µA
Alarm current at 9V	17µA	17µA	17µA
Alarm indication			
Normal operating temperature (no condensation or icing)	-20 to +60°C	-20 to +90°C	-20 to +90°C
Max wind continuous	Not affected	Not affected	Not affected
Remote output (R-) characteristics	Current sink to -ve line, limited to 17mA <i>Note: when using a remote indicator a current-limiting resistor may be required</i>		

<i>The data above will be the same for the other classes (BR,CR,CS)</i>					
Series 65 relay bases					
Relay base type	Standard	Auxiliary	EOL 12V	EOL 24V	12V Base
Part No	03-NA-037R	03-NA-037B	03-NA-037C	03-NA-037D	03-NA-037E
Supply Voltage	9 to 33V	9 to 33V	9 to 18V	16 to 33V	16 to 33V
Normal operating temperature (No condensation or icing)	-20 to +70°C	-20 to +70°C	-20 to +70°C	-20 to +70°C	-20 to +70°C
Relay ratings	30W, 50VA	30W, 50VA	30W, 50VA	30W, 50VA	30W, 50VA
Maximum switching power	1A (resistive load)	1A (resistive load)	1A (resistive load)	1A (resistive load)	1A (resistive load)
Maximum switching current	50V AV	50V AV	50V AV	50V AV	50V AV
Maximum switching voltage	10 µA, 10mV DC	10 µA, 10mV DC	10 µA, 10mV DC	10 µA, 10mV DC	10 µA, 10mV DC
Minimum capability	<6V	<6V	<6V	<6V	<6V
Dropout voltage					

Class Application	Static Response Temperature °C		Standard Part No	Flashing LED Part No	Flashing LED/Reed Switch - Part No
	typical	max			
A1R	25	50	03-NA-034A	03-NA-035A	03-NA-036A
BR	40	65	03-NA-034B	03-NA-035B	03-NA-036B
BR	40	65	03-NA-034C	03-NA-035C	03-NA-036CR
BR	40	65	03-NA-034D	03-NA-035D	03-NA-036CS

