

# SDX-751EM

## Low Profile Optical Analogue Addressable Sensor

Section: Intelligent/Addressable Devices

### FEATURES

- **Sleek low profile design**
- **Uses common sensor base**
- **Analogue addressable communications**
- **Stable communication technique with high noise immunity**
- **Low standby current**
- **Rotary DECADE 01 to 99 address switches**
- **Remote LED output as standard**
- **Dual LED design provides 360° viewing angle**
- **Visible LED's blink every time the sensor is addressed (optional), and illuminate steady on alarm**
- **Built-in functional test switch activated by external magnet**
- **Optional Relay, Isolator, or Sounder bases**
- **Tamper-resistant feature**
- **LPCB (EN54 part 7) and VdS approved**

### GENERAL

The SDX-751EM is an analogue addressable, low profile Optical smoke sensor designed for use with any NOTIFIER protocol fire alarm control panel.

This analogue addressable sensor enables the control panel to provide the operator with a pinpoint description of where the fire is located. The control panel is capable of not only knowing the sensor's location but exactly how much smoke is in the chamber of the sensor.

The sensor may be set for different sensitivity settings appropriate to the environment of its location.

The SDX-751EM analogue addressable Optical sensor's unique sensing chamber is designed with superior signal to noise ratio. The optical chamber is engineered to sense the presence of smoke produced by a wide range of combustion sources.

### INSTALLATION

The SDX-751EM plug-in Optical smoke sensor uses a common base to simplify installation, service, and maintenance.

A special tool allows maintenance personnel to plug-in and remove detectors without using a ladder.

Mounting hardware and installation instructions are provided with each device.



This document is not intended to be used for installation purposes. Every care has been taken in the preparation of this document but no liability can be accepted for the use of the information therein. Design features may be changed or amended without prior notice. For more information, contact **NOTIFIER**. Charles Avenue, Burgess Hill, West Sussex, RH15 9UF. United Kingdom  
 Phone: +44 (0) 1444 230 300 Fax: +44 (0) 1444 230 888

**ISO9001**  
 Design, Manufacture and Supply  
 to Quality Management Systems  
 Certified to ISO9001:1994



## SPECIFICATIONS

### • Dimensions

- ✓ Height: 43 mm installed in B501 Base.
- ✓ Diameter: 102 mm installed in B501 Base.
- ✓ Weight: 102 g.

### • Current Consumption

- ✓ 230  $\mu$ A @ 24 VDC (without communication); 300  $\mu$ A @ 24 VDC (one communication every 5 sec. with LED enabled).
- ✓ Maximum Alarm Current: 6.5 mA @ 24VDC (with LED enabled).

### • Operating Voltage

- ✓ 15 to 32 VDC peak.

### • Environmental Limits

- ✓ -20°C to 60°C operating temperature.
- ✓ -30°C to 80°C storage or short term temperature.
- ✓ 10% to 93%, non-condensing relative humidity

## ORDERING INFORMATION

Part No.	Description
SDX-751EM	Intelligent Optical Smoke Sensor. Mounting options specified below.

### Base:

B501	Standard Sensor Base.
B524IE	Isolator Base.
B524IEFT	FET Isolator Base.
B524RE	Relay Base.
IBS3	Addressable, loop powered base sounder, see Accessories for Cover Plate options.

### Accessories:

SMK400	Surface mounting kit provides for entry of surface wiring conduit. For use with B501 base only.
RMK400	Recess mounting kit. For use with B501 base only.
IBS-LIDR	Loop Powered Base Sounder Cover Plate, Red. For use with IBS3 base when sensor is not installed.
IBS-LIDW	Loop Powered Base Sounder Cover Plate, White. For use with IBS3 base when sensor is not installed.

## Wiring Diagram (Standard Base)



